


Smoke Alarm

10 Year Lithium Cell Powered



Communication Capability

Model EIB605TYC Photoelectric

- 10 Year Lithium cell will outlast the useful lifespan of the alarm
- Interconnect up to 12 battery powered alarms
- Optional upgrade to  interconnect
- Early detection to all standard domestic fires types
- Built-in high audibility warning sounder
- Large Easy to use Test/Hush button
- Hush Feature allows nuisance alarm control
- Easy to install twist-on base design
- Aesthetically pleasing, compact design
- Innovative and robust optical chamber design
- Certified to AS3786
- EN 14604:2005 3rd party approved
- 5 year Guarantee



Product Description

The EIB605TYC is a Photoelectric (Optical) Smoke Alarm using the light scatter principle, giving a quick response to all standard domestic fire types.


There is no requirement to replace cells as the Lithium cells will power the alarm for more than 10 years. The non replaceable cell and tamperproof design limits the possibility of the alarm being disabled.

The EIB605TYC is designed for simple installation, commissioning and maintenance.

The EIB605TYC has a large, easy to use, combined Test/Hush button enables full testing of the alarm and the ability to silence nuisance alarms.

The EIB605TYC has an innovative high performance optical chamber with integral fixed insect screen reducing the possibility of nuisance alarms.

The EIB605TYC maybe hardwire interconnected to twelve battery powered alarms enabling all alarms to sound if just one of the interconnected alarms should be triggered.

The EIB605TYC modular design allows it to be upgraded for  functionality with the addition of the EIB605MTYRF Radio frequency module.

Operation

- The smoke detector will activate the built in sounder upon sensing smoke particles. It will automatically reset and silence the alarm when the smoke particles are no longer present in the chamber.
- The red indicating LED will flash once every 40 seconds to show that the alarm is powered and it has performed an automatic self-test.
- The built in sounder will provide a minimum sound output of 85dB at 3m.
- Pressing and holding the "Test/Hush" button will perform a self test and sound the horn – checking the chamber, electronics and horn.
- Momentarily pressing the "Test/Hush" button when an alarm is sounding will set the alarm into "HUSH" mode. This reduces the sensitivity for a period of 10 minutes, after which the alarm automatically resets – providing control over nuisance alarms.
- The alarm is not powered until it is connected to the twist on base, thus avoiding battery power consumption during storage and prior to installation.



Australia Head Office: 4 Pike Street Rydalmere NSW 2116
Ph+61 2 9684 1466 **Fx**+61 2 9684 4146 **Toll Free** 1300 78 FIRE


New Zealand Unit 106, The Zone, 23 Edwin Street Mount Eden 1024
Ph+64 9 638 4644 **Fx**+64 9 6384645 **Toll Free** 0800 220 007

AUS Web: www.brooks.com.au **NZ Web:** www.brooks.co.nz


Model EIB605TYC Optical

Technical Specification

Sensor:	Optical, uses light scatter from smoke particles
Sensitivity:	Complies with the requirements of BS EN 14604: 2005
Airspeed:	Essentially immune to the effect of airspeed.
Button Test:	Simulates the effect of smoke to check the chamber, electronics and horn.
Hush:	Silences nuisance alarm. Automatically resets after approximately 10 minutes
Supply Voltage:	10 Year Lithium Cells with 2,000mAh capacity.
Power-On Indicator:	Red LED flashes through cover every 40 seconds

Alarm:	Piezoelectric-horn (built-in)
Alarm Sound Output:	85dB (minimum) at 3m
Temperature Range:	0 to 40°C
Humidity Range:	15% to 95% Relative Humidity – non condensing
Interconnect:	Hardwire interconnect up to 12 battery powered alarms. A combination of up to 12 battery and Mains powered alarms maybe  interconnected
Fixing:	Screw fixings supplied
Dimensions:	115mm (diameter) x 45mm (height)
Weight:	200 grams
Warranty:	5 year (limited) warranty
Approvals:	Certified to AS3786 VdS approved BS EN14604:2005, CE approved, Manufactured to ISO 9001:2000 quality standards.

Installation & Placement



Alarms should be placed in accordance with the general guidelines shown in the diagram above. These recommendations are based on the problem of areas of “dead air” close to corners of rooms and apexes of ceilings, which could result in the prevention of smoke reaching the smoke detector.

Please consult the Instruction Leaflet supplied with the EIB605TYC for detailed instructions as to how to correctly install and position the smoke detector.

Specifications are subject to change

Important Precaution:

Do not install the actual smoke/heat alarm itself in new or renovated buildings until all work is completed (including floor coverings) and the building has been fully cleaned. (Excessive dust and debris from building work can contaminate the smoke chamber and cause problems, and it will also invalidate the guarantee). If it must be installed, cover it completely, particularly around the edges, with a dust cover (eg. a plastic bag), until all cleaning is finished..

Specifications are subject to change



Australia Head Office: 4 Pike Street Rydalmere NSW 2116
Ph+61 2 9684 1466 **Fx**+61 2 9684 4146 **Toll Free** 1300 78 FIRE

New Zealand Unit 106, The Zone, 23 Edwin Street Mount Eden 1024
Ph+64 9 638 4644 **Fx**+64 9 6384645 **Toll Free** 0800 220 007

AUS Web: www.brooks.com.au **NZ Web:** www.brooks.co.nz